










LAMP INFORMATION

RUNNING & STARTING CURRENTS

The universal European code for lamps is generally used throughout this catalogue for consistency. Further details below.

	LAMP TYPE	CAP	WATTAGE	CIRCUIT WATTAGES CCG	WATTAGES ECG	STARTING CURRENT*	RUNNING CURRENT*
	CMH	G8.5	20W		24W		0.10A
	CDM-T	G12	35W	43W	39W	0.35A	0.24A
	CDM-T	G12	70W	89W	74W	0.80A	0.50A
	CDM-T	G12	150W	170W		1.50A	1.00A
	HIT-DE	Rx7s	70W	89W	74W	0.80A	0.50A
	HIT-DE	Rx7s	150W	170W		1.50A	1.00A
	HIT-DE	Fc2	250W	275W		2.00A	1.50A
	HIT-DE	Fc2	400W	440W		3.80A	2.40A
	SDW-T	PG12	35W	41W		0.70A	0.20A
	SDW-T	PG12	50W	62W		0.80A	0.35A
	SDW-T	PG12	100W	115W		1.30A	0.55A
	TC-D	G24d-1	10/13W	17W	14W	0.08A	0.07A
	TC-D	G24d-2	18W	24W	20W	0.11A	0.10A
	TC-D	G24d-3	26W	34W	28W	0.16A	0.14A
	TC-T	GX24d-1	13W	17W	14W	0.08A	0.07A
	TC-T	GX24d-2	18W	24W	20W	0.11A	0.10A
	TC-T	GX24d-3	26W	34W	28W	0.16A	0.14A
	TC-TE	GX24q-3	32W		37W		0.17A
	TC-TE	GX24q-4	42W		48W		0.22A
	TC-TE	GX24q-5	57W		62W		0.29A
	TC-F	2G10	36W	46W	39W	0.20A	0.17A
	TC-L	2G11	18W	24W	19W	0.12A	0.10A
	TC-L	2G11	24W	30W	27W	0.14A	0.11A
	TC-L	2G11	36W	43W	39W	0.20A	0.17A
	TC-L	2G11	55W		62W		0.27A
	TC-L	2G11	80W		86W		0.36A

*Starting and running current applicable to fully power-factor corrected conventional control gear as used in all SOVEREIGN® & MEYER luminaires. Above information taken from lamp and gear manufacturers technical data for guidance purposes only.